

MIC iMIX

5 ZONE PAGING STATION FOR IMIXS ZONE ROUTER

The MIC iMIX is a five-zone paging microphone featuring intuitive zone selection buttons compatible with the iMIX 5 system. Users can select individual zones or all zones for announcements. The device supports immediate talk or a pre-announcement chime, configurable through DIP switches. It also includes a 3.5 mm stereo TRS jack input for connecting a local audio source.

Technical Specifications	MIC iMIX
Microphone type	Condenser microphone
Polar pattern	Cardioid
Frequency response	-3 dB 150 Hz - 22kHz
Control	6 x illuminated zone select buttons (1-5, all zones) 1 x Talk button
Input impedance	Mic: 600 Ω , Aux: 50k Ω
Output impedance	Balanced 600 Ω
Input level Mic	-46 dBV, Aux: -10 dBV
Output level	10 dB
S/N ratio	-60 dB
Connectors	RJ45, 24 V DC power jack, 3.5 mm stereo TRS
Interface	RS-485
Max. connection length	500 m
Power supply	24 V DC, 500 mA
Dimensions	460 mm x 140 mm x 115 mm
Weight	670 g

