

## Go Series G440

### **4K 8MP 4G LTE Wireless Battery/Solar Powered PT Outdoor Camera with Smart Detection & Color Night Vision**

- 4K 8MP Ultra HD
- 4G LTE Network
- Color Night Vision

## **Specifications**

<b>Video &amp; Audio</b>	
Image Sensor	1/2.7" CMOS Sensor
Video Resolution	3840 x 2160 (8 Megapixel)@15fps
Video Compression	H.265
Field of View	Fixed Lens, Horizontal: 90°, Vertical: 47° , Diagonal: 110°
Infrared Night Vision	Up to 10 Meters (33ft) (LED: 2pcs/1.2W/850nm)
Color Night Vision	Spotlight: 2pcs/2.4W/6500K
Audio	Two-Way Audio
<b>Alarm</b>	
Smart Alarm	PIR/person/vehicle/animal detection
PIR Detecting Distance	Adjustable up to 10m (33 ft)
PIR Detecting Angle	120° Horizontal
Audio Alert	Customized Audio Alerts
Recording	Motion-Triggered Recording

Other Alerts	Instant Email Alerts and Push Notifications
<b>Pan &amp; Tilt</b>	
Pan &Tilt	355° Pan, 140° Tilt
Preset Points	Supports 1 guard position & up to 32 preset positions
<b>3G/4G Bandwidth</b>	
Frequency Bands	<ul style="list-style-type: none"> <li>• Europe Version: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8</li> <li>• USA Version: LTE FDD: B2/B4/B5/B12/B13/B14/B66/B71</li> <li>• Australia Version: LTE FDD: B1/B3/B5/B7/B8/B28 WCDMA: B1/B5/B8</li> </ul>
<b>Power</b>	
Battery	21.6Wh Rechargeable Battery (Battery life varies based on settings, usage & temperature)
Solar	Reolink Solar Panel 2
DC Power	USB Type-C port
<b>Storage</b>	
Local Storage	microSD Card (32GB included, max. 128GB)
Cloud Storage	Reolink Cloud (only available in some countries)
<b>Software Features</b>	
OS Supported	
Protocols & Standards	
Max. User Access	
<b>Smart Home</b>	
Smart Home	Google Assistant
<b>Working Environment</b>	

Operating Temperature	-10 to 55° C (14° to 131° F)
Weather Resistance	IP64
<b>Size &amp; Weight</b>	
Size	Φ98 x 122mm
Weight (Battery included)	496g
<b>Warranty</b>	
Limited Warranty	2-year limited warranty. For support, visit <a href="https://support.reolink.com/hc/en-us/">https://support.reolink.com/hc/en-us/</a>

## Gallery & Specs



1. Speaker
2. IR LEDs
3. Spotlights
4. Daylight Sensor
5. Lens
6. Status LED
7. PIR Motion Sensor
8. Built-in Microphone



1. IR LEDs
2. Status LED
3. Daylight Sensor
4. Lens
5. Built-in Mic
6. PIR Motion Sensor
7. USB-C Port
8. Speaker